

DT , 240 kA, 480 V, 3PhΔ 3W+G

Data Solutions

???

DTX240B480D



nVent ERICO DTX240 (SPD)
IEC I II UL 1 2
B DTX240
240 kA C
(MCC) (HVAC) nVent ERICO DTX240
NEMA®-4X

??



??

(UL)

SPD

RS-485

10

????

(Un): 480 V

3Ph? 3W+G

(Uc): 510 VAC

(In)?UL: 20kA 8/20 ?s

(Imax)??: 240kA 8/20 ?s

(Iimp)??: 12.5kA 10/350 ?s

??: 50 – 60Hz

??????? (VPR)?L-G: 1800V

??????? (VPR)?L-L: 1800V

????: L-PE

????? (SCCR): 200kA

????? (In)?IEC: 40kA 8/20 ?s

????? (Up)?IEC: 1200 V @ 20 kA; 3000 V @ 100 kA

????? (Iscrr): 50kA

?: 240 to 80°C

????: ??? PC ?

?????: NEMA®-4X; UL® 50E 4 ?

????: 2.5 – 16mm²

?: 8 ?????

?????????: 2.0 A @ 240 V

????: ??C ??

????: ??????????; ??? LED; ???; OLED ???; ??/TOV ??????

?: ??????????

?????: CSA C22.2 ? 269.2 ?; UL® 1449 ? 5 ? 1/2 ???20 kA ??

?: ANSI®/IEEE® C62.41.2-2002 A ??B ??C ?; ANSI®/IEEE® C62.41.1-2002 A ??B ??C ?; ANSI®/IEEE® C62.45-2002 A ??B ??C ?; EN 61643-11 2 ?; IEC® 61643-11 II ?

?? (D): 98.3mm

?? (H): 330.7mm

?? (W): 222.5mm


????: 5.3kg

????: DT2510DTXM

??????

????????????DTX240FP ? DTX240SM

?



??

???? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????? nVent
??



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE