


□□□ , □□ -□□ , 230 A IEC, □ ,
□□□□□

Data Solutions

???

SB160AL



nVent ERIFLEX

????????????????????(???????)??/?????? DIN

????/????????????????????????????????

????????????????????4????nVent ERIFLEX Flexibar Advanced,
??IBSB Advanced ????

??



??

??????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ?????

???????????????

????????????????????????????

???????????

??????????????????

??????????????????

????? DIN ???????????

??????????

??? 95%

????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

?????????? ??????

???: 561162
?: ??
?: ??-??
????????IEC: 230A
?: ?; ???
????????IEC: 70 mm²
????????IEC: 70 mm²
????? (ICW) 1 ?: 14.4kA
???????IEC: 230A
???????UL/CSA: 200A
????? (Ipk): 42kA
??????? (ICC): 20kA
????? (SCCR): 100kA
???????IEC (Ui): 1000; 1500
???????UL (Vin): 1000
???????: 1
?????????: 35-70 mm²; #2 - 3/0
?????????: 35-70 mm²; #2 - 3/0
???????: 1
???????? - ??: 35-70 mm²
?? (D): 55mm
?? (H): 111mm
?? (W): 27.7mm
????: 0.1kg
?????: UL® 1059
?: IEC® 60947-7-1
?????: IP 20
?????: UL® 94V-0



???? nVent ?????????????? nVent ??????? www.nvent.com ?????????? nVent ?????????????????????????????? nVent
??



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE