


□□□ , □□ -2□□□ , 400 A IEC, □ ,
□□□□□

Data Solutions

???

SB2C250



nVent ERIFLEX

????????????????????(???????)??/?????? DIN

????/????????????????????????????????

????????????????????4????nVent ERIFLEX Flexibar Advanced,
??IBSB Advanced ?????

??



??

???????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ?????

????????????????

????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????

????????

?? 95%

????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ?? R22 ?? HL2 ?

????????? ?????

???: 561170

??: ??-2 ???

????????IEC: 400A

??: ?; ???

????????IEC: 120 mm²

????????IEC: (2) 120 mm²

?????? (ICW) 1 ? : 14.4kA

???????IEC: 550A

??????UL/CSA: 255A

?????? (I_{pk}): 42kA

????????? (ICC): 20kA

?????? (SCCR): 100kA

??????IEC (Ui): 1000; 1500

???????UL (V_{in}): 1000

??????: 1

??????????: #6 - 250 ????; 35 - 120 mm²

??? DLO ???: #6 - 2/0

?????????: (2) 35 - 120 mm²

??????: 2

???????? - ??: (2) 35 - 120 mm²

??????: (2) #6 - 250 ????

?? (D): 83mm

?? (H): 148mm

?? (W): 35mm

????: 0.5kg

?????: UL® 1953

?: IEC® 60947-7-1

?????: IP 20

?????: UL® 94V-0

SBF250?SB250SPCR?????UL1953????? ??UL® 1953??????????1250VAC/DC?

????????????????7%

1111111111111111

????*?? (°C) ????? 85°C ?????

???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47

*??????????



???? nVent ?????????????? nVent ??????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??/?????????????



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE