

□□□ , □□ -□□ , 500 A IEC, □ , □□□□□

## Data Solutions

???

### SB400



nVent ERIFLEX  
????????????????????(???????)??/?????? DIN  
?????/??  
????????????????????4????nVent ERIFLEX Flexibar Advanced,  
??IBSB Advanced ?????

??



??

???????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ??????
?????????????????
??
???????????????
???????????????????????
???????????????????????
????? DIN ????????????????
???????????????
?? 95%
????????????????????????????(RoHS) ??
?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?
???????????? ????????

????

???: 561152

?: ??

?: ??-??

????????IEC: 500A

?: ?; ???

????????IEC: 240 mm<sup>2</sup>

????????IEC: 240 mm<sup>2</sup>

????? (ICW) 1 ? : 28.8kA

????????IEC: 500A

????????UL: 335A

????? (Ipk): 51kA

???????? (ICC): 24.3kA

????? (SCCR): 100kA

????????IEC (Ui): 1000; 1500

????????UL (Vin): 1250

????????: 1

?????????: 95 - 240 mm<sup>2</sup>; 3/0 - 400 kcmil

?????????: 95 - 240 mm<sup>2</sup>; 3/0 - 400 kcmil

????????: 1

???????? - ??: 95 - 240 mm<sup>2</sup>

?? (D): 82mm

?? (H): 146.4mm

?? (W): 41.5mm

????: 0.51kg

?????: UL® 1059

?: IEC® 60947-7-1

?????: IP 20

?????: UL® 94V-0

??????

SBF250?SB250SPCR?????UL1953????? ?UL® 1953????????1250VAC/DC?

????????????????????7%

□□□□□□□□□□										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*???????????										

?



??

??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????? nVent  
 ???/?????????????



?????????:  
 CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE