

□□□ , □□ -□□ , 250 A IEC, □ ,
□□□□□

Data Solutions

???

SB160



nVent ERIFLEX
 ??????????????????????(???????)???/??????? DIN
 ?????/????????????????????????????????????
 ?????????????????????4????nVent ERIFLEX Flexibar Advanced,
 ??IBSB Advanced ?????

??



??

???????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ??????

????????????????

????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????

????????

??? 95%

????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

????????? ??????

???: 561151
?: ??
?: ??-??
????????IEC: 250A
?: ?; ???
????????IEC: 70 mm²
????????IEC: 70 mm²
????? (ICW) 1 ?: 14.4kA
???????IEC: 250A
???????UL: 200A
????? (Ipk): 42kA
???????? (ICC): 20kA
????? (SCCR): 100kA
???????IEC (Ui): 1000; 1500
???????UL (Vin): 1000
??????? : 1
??????????? : 35-70 mm²; #2 - 3/0
??????????? : 35-70 mm²; #2 - 3/0
??????? : 1
???????? - ??: 35-70 mm²
?? (D): 55mm
?? (H): 111mm
?? (W): 27.7mm
????: 0.18kg
?????: UL® 1059
?: IEC® 60947-7-1
?????: IP 20
?????: UL® 94V-0

SBF250?SB250SPCR?????UL1953????? ??UL® 1953??????????1250VAC/DC?



???? nVent ?????????????? nVent ??????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??/?????????????



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE