


TD 160 A, 1 Line Side Connection(s), 11 Load Side Connection(s), 50 mm

Data Solutions

???

TD-160A



??



??

- ??????????
- ??????????
- ???????
- ???????
- ????? DIN ????????????
- ?????????
- ???????
- ??????
- ??????????
- ????????????????????????????????(RoHS) ??
- ?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

???

????

???: 563200

??: ???; ??

??????IEC: 160A

????? (ICW) 1 ? : 8.2kA

????? (Ipk): 35kA

??????IEC (Ui): 690V

???????: 1

?????????: 10 - 50 mm²

????????? - ??: 10 - 50mm²

???????: 11

?????????: (1) 2,5 - 6 ????; (7) 2,5 - 16 mm²; (3) 10 - 35 mm²

????????? - ??: (1) 1,5 - 6 ????; (7) 1,5 - 16 mm²; (3) 10 - 25 mm²

?? (D): 50mm

?? (H): 90mm

?? (W): 175mm

????: 0.61kg

?????: UL® 94V-0



?: IEC® 60947-7-1

??????

????????????????

????*?? (°C) ????? 85°C ?????	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*????????										

?



??

??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??/?????????????



??????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE