



?? HOFFMAN ????????

Provide positive internal safety lockout on electrical enclosures while the equipment is energized. When energized, these interlocks prevent the door handle from being turned to open the door.

Catalog numbers AEK115, AEK230 and AEK460 are used with standard HOFFMAN door latching mechanisms. Fit either clockwise or counterclockwise handles in the following enclosures:
 1. All two-door Type 4 and 12 enclosures
 2. All Type 4X with 3-point latch enclosures
 3. Free-standing Type 12 enclosures
 4. All one-door Type 12 enclosures with latch kits installed. The interlocks will fit the following enclosures, but modifications are required. Consult the factory for more information.
 1. Two-door Type 12 enclosures for flange-mounted disconnects
 2. Heavy duty free-standing Type 12 enclosures for flange-mounted disconnects
 3. Modular Type 12 enclosures for flange-mounted disconnects
 4. Multi-door Type 12 enclosures

The interlocks will also fit most HOFFMAN custom enclosures with door latching mechanisms similar to the mechanisms used on the preceding enclosures. AC electrical interlocks will not fit Bulletin A25 and A26 enclosures. Interlocks are not designed to be used in place of the standard door or cover latch.

Catalog numbers AEK115NDH, AEK230NDH and AEK460NDH are designed to be used on some HOFFMAN enclosures and boxes which have exterior latching only. When energized, these interlocks will prevent the enclosure door from being opened. They fit on the door or cover of the following enclosures and maintain UL Type 4, 4X and 12 when properly installed per HOFFMAN instructions:
 1. One-door Type 4 and 4X enclosures
 2. Two-door Type 4 and 4X enclosures
 3. One-door Type 12 enclosures
 4. Larger sizes of Hinge-Cover junction boxes
 5. Type 1 and large Type 1 enclosures



????

UL 508A Component Recognized; File No. E61997
 CSA ??????? 42186

??

????????????????????????????????

????????????????????????????????

??????????

???????????????? AEK ?????????????????????????????????

?? AEK NDH ?????????????????????????????

????

Table 1/1

???	???	??	??	□ 60 Hz □□□□□□ □	□ 50 Hz □□□□□□ □	□ 50Hz □□□□□
AEK460NDH	26760	???	??	0.025 / 0.16A	0.030 / 0.18A	440V
AEK230NDH	26750	???	??	0.050 / 0.32A	0.060 / 0.35A	220V
AEK115NDH	26190	???	??	0.100 / 0.63A	0.120 / 0.69A	110V

??

???? nVent ?????????????????? nVent ??????? www.nvent.com ?????????????? nVent ?????????????????????????????????????? nVent
 ???



???????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE